

Annex to declaration of accreditation (scope of accreditation)
 Normative document: EN ISO/IEC 17025:2017
 Registration number: **K 052**

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020** to **01-03-2022**

Replaces annex dated: **19-02-2020**

Location(s) where activities are performed under accreditation

Head Office

Storkstraat 2 - 4
 2722 NN
 Zoetermeer
 Nederland

Location	Abbreviation/ location code
Storkstraat 2 – 4 2722 NN Zoetermeer The Netherlands	ZTM

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
LF 0 0	DC/LF Electricity				
LF 1 0	Direct Voltage				ZTM
	10 µV – 100 µV		$5 \cdot 10^{-3} \cdot U$	Measurement	
	100 µV – 1 mV		$5 \cdot 10^{-4} \cdot U$		
	1 mV – 10 mV		$1 \cdot 10^{-4} \cdot U$		
	10 mV – 100 mV		$3 \cdot 10^{-5} \cdot U$		
	100 mV – 2 V		$7 \cdot 10^{-6} \cdot U$		
	2 V – 20 V		$3 \cdot 10^{-6} \cdot U$		
	20 V – 1 kV		$6 \cdot 10^{-6} \cdot U$		

¹ Calibration and Measurement Capability (CMC): Demonstrated measurement uncertainty, with coverage probability of 95%, in a given measurement point or measurement range. Measurement uncertainty, *U*, is calculated according to EA-4/02 "Evaluation of the Uncertainty of Measurement in Calibration".

This annex has been approved by the Board of the Dutch Accreditation Council, on its behalf,

J.A.W.M. de Haas
 Director of Operations

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	10 mV – 100 mV		$4 \cdot 10^{-5} \cdot U$	Measurement	On site
	100 mV - 1 kV		$1 \cdot 10^{-5} \cdot U$		
	0.1 V		$1 \cdot 10^{-6} \cdot U$	Measurement and generation	
	1 V		$9 \cdot 10^{-7} \cdot U$		
	1.018 V		$9 \cdot 10^{-7} \cdot U$		
	10 V		$7 \cdot 10^{-7} \cdot U$		
	100 V		$7 \cdot 10^{-7} \cdot U$		
	1000 V		$1.2 \cdot 10^{-6} \cdot U$		
	10 mV – 100 mV		$6 \cdot 10^{-5} \cdot U$	Generation	
	100 mV – 2.2 V		$1.5 \cdot 10^{-5} \cdot U$		
	2.2 V – 22 V		$7 \cdot 10^{-6} \cdot U$		
	22 V – 1 kV		$1 \cdot 10^{-5} \cdot U$		
	10 mV – 330 mV		$3 \cdot 10^{-5} \cdot U$	Generation	On site
	330 mV - 1 kV		$2 \cdot 10^{-5} \cdot U$		
	Conversion factor (0.001 – 1) V/V		$1 \cdot 10^{-3} \cdot U/U$	also on site	
LF 1 2	Direct Voltage ratio				ZTM
	(0.001 – 1) V/V		$1 \cdot 10^{-3} \cdot U/U$	primary voltage 100 mV to 1000 V, secondary voltage 0.1 mV to 1000 V	Also on site
LF 1 3	Direct High Voltage				ZTM
	1 kV – 30 kV		$8 \cdot 10^{-4} \cdot U$	Measurement	Also on site
	1 kV – 30 kV		$1 \cdot 10^{-3} \cdot U$	Generation	Also on site
LF 1 4	Pulse Amplitude				ZTM

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	2mV	10 Hz	$1 \cdot 10^{-3} \cdot U$	Generation in 1MΩ	
	2mV	100Hz/1kHz	$5 \cdot 10^{-4} \cdot U$	Generation in 1MΩ	
	5mV – 100V	10Hz/100Hz/1kHz	$5 \cdot 10^{-4} \cdot U$	Generation in 1MΩ	
	2mV – 100V	10 Hz - 1 kHz	$5 \cdot 10^{-4} \cdot U$	Measurement	
LF 2 0	Direct Current			Measurement and generation	ZTM
	10 μA – 1 mA		$1 \cdot 10^{-5} \cdot I$		
	1 mA – 150 mA		$2.5 \cdot 10^{-5} \cdot I$		
	0.15 A – 15 A		$2 \cdot 10^{-5} \cdot I$		
	15 A – 20 A		$5 \cdot 10^{-5} \cdot I$		
	20 A – 30 A		$2 \cdot 10^{-4} \cdot I$		
	10 μA – 100 μA		$4 \cdot 10^{-4} \cdot I$	Generation	On site
	100 μA – 10 mA		$2 \cdot 10^{-4} \cdot I$		
	10 mA – 100 mA		$2 \cdot 10^{-4} \cdot I$		
	0.1 A – 1 A		$3 \cdot 10^{-4} \cdot I$		
	1 A – 10 A		$5 \cdot 10^{-4} \cdot I$		
	10 A – 20 A		$1 \cdot 10^{-3} \cdot I$		
	10 μA – 100 μA		$4 \cdot 10^{-5} \cdot I$	Measurement	On site
	100 μA – 10 mA		$4 \cdot 10^{-5} \cdot I$		
	10 mA – 100 mA		$5 \cdot 10^{-5} \cdot I$		
	0.1 A – 1 A		$1 \cdot 10^{-4} \cdot I$		
	1 A – 20 A		$1.3 \cdot 10^{-4} \cdot I$		
	100 mA – 20 A		$3.5 \cdot 10^{-3} \cdot I$	Generation, only for current clamps / probes	Also on site
	20 A – 1000 A		$8 \cdot 10^{-3} \cdot I$		
	Conversion factor (0.001 – 1) V/A		$3.5 \cdot 10^{-3} \cdot U/U$		Also on site

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
LF 2 2	Direct Current Ratio (0.001 – 1) V/A		$3.5 \cdot 10^{-3} \cdot U/I$	primary current 100 mA to 1000 A, secondary voltage 0.1 mV to 1000 V	ZTM Also on site
LF 3 0	Alternating Voltage			Measurement and generation	ZTM
	60 mV	10 Hz – 20 Hz	$3 \cdot 10^{-4} \cdot U$	Generation > 200V at 50 Hz – 1 kHz	
		20 Hz – 40 Hz	$1.5 \cdot 10^{-4} \cdot U$		
		40 Hz – 20 kHz	$1 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$2 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$6 \cdot 10^{-4} \cdot U$		
		100 kHz – 500 kHz	$6 \cdot 10^{-4} \cdot U$		
		500 kHz – 1 MHz	$1.5 \cdot 10^{-3} \cdot U$		
	100 mV – 200 mV	10 Hz – 20 Hz	$2.5 \cdot 10^{-4} \cdot U$		
		20 Hz – 40 Hz	$1 \cdot 10^{-4} \cdot U$		
		40 Hz – 20 kHz	$1 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$2 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$2 \cdot 10^{-4} \cdot U$		
		100 kHz – 500 kHz	$5.5 \cdot 10^{-4} \cdot U$		
		500 kHz – 1 MHz	$1.4 \cdot 10^{-3} \cdot U$		
	200 mV – 600 mV	10 Hz – 20 Hz	$2.5 \cdot 10^{-4} \cdot U$		
		20 Hz – 40 Hz	$1 \cdot 10^{-4} \cdot U$		
		40 Hz – 20 kHz	$5 \cdot 10^{-5} \cdot U$		
		20 kHz – 50 kHz	$1 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1 \cdot 10^{-4} \cdot U$		
		100 kHz – 500 kHz	$5 \cdot 10^{-4} \cdot U$		
		500 kHz – 1 MHz	$1.4 \cdot 10^{-3} \cdot U$		
	600 mV – 2 V	10 Hz – 20 Hz	$2 \cdot 10^{-4} \cdot U$		
		20 Hz – 40 Hz	$1 \cdot 10^{-4} \cdot U$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		40 Hz – 20 kHz	$5 \cdot 10^{-5} \cdot U$		
		20 kHz – 50 kHz	$1 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1 \cdot 10^{-4} \cdot U$		
		100 kHz – 500 kHz	$5 \cdot 10^{-4} \cdot U$		
		500 kHz – 1 MHz	$1.3 \cdot 10^{-3} \cdot U$		
	2 V – 20 V	10 Hz – 20 Hz	$2 \cdot 10^{-4} \cdot U$		
		20 Hz – 40 Hz	$1 \cdot 10^{-4} \cdot U$		
		40 Hz – 20 kHz	$5 \cdot 10^{-5} \cdot U$		
		20 kHz – 50 kHz	$1 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1 \cdot 10^{-4} \cdot U$		
		100 kHz – 500 kHz	$5 \cdot 10^{-4} \cdot U$		
		500 kHz – 1 MHz	$1.6 \cdot 10^{-3} \cdot U$		
	20 V – 200 V	10 Hz – 20 Hz	$2 \cdot 10^{-4} \cdot U$		
		20 Hz – 40 Hz	$1 \cdot 10^{-4} \cdot U$		
		40 Hz – 20 kHz	$5 \cdot 10^{-5} \cdot U$		
		20 kHz – 50 kHz	$1 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1 \cdot 10^{-4} \cdot U$		
	200 V – 1,000 V	10 Hz – 20 Hz	$2 \cdot 10^{-4} \cdot U$	Generation > 200V at 50 Hz – 1 kHz	
		20 Hz – 40 Hz	$1 \cdot 10^{-4} \cdot U$		
		40 Hz – 20 kHz	$1 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$2 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$2 \cdot 10^{-4} \cdot U$		
	1 mV – 10 mV	1 Hz – 40 Hz	$2 \cdot 10^{-3} \cdot U$	Measurement	On site
		40 Hz – 1 kHz	$2 \cdot 10^{-3} \cdot U$		
		1 kHz – 20 kHz	$2 \cdot 10^{-3} \cdot U$		
		20 kHz – 50 kHz	$3 \cdot 10^{-3} \cdot U$		
		50 kHz – 100 kHz	$6 \cdot 10^{-3} \cdot U$		
		100 kHz – 300 kHz	$4 \cdot 10^{-2} \cdot U$		
	10 mV – 10 V	1 Hz – 20 kHz	$3 \cdot 10^{-4} \cdot U$	Measurement	On site

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020** to **01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		20 kHz – 50 kHz	$5 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$9 \cdot 10^{-4} \cdot U$		
		100 kHz – 300 kHz	$3 \cdot 10^{-3} \cdot U$		
		300 kHz – 1 MHz	$9 \cdot 10^{-2} \cdot U$		
		1 MHz – 2 MHz	$1.3 \cdot 10^{-2} \cdot U$		
	10 V – 100 V	1 Hz – 20 kHz	$4 \cdot 10^{-4} \cdot U$	Measurement	On site
		20 kHz – 50 kHz	$5 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1.3 \cdot 10^{-3} \cdot U$		
		100 kHz – 300 kHz	$4 \cdot 10^{-3} \cdot U$		
		300 kHz – 1 MHz	$1.3 \cdot 10^{-2} \cdot U$		
	100 V – 1,000 V	1 Hz – 1 kHz	$5.5 \cdot 10^{-4} \cdot U$	Measurement	On site
		1 kHz – 20 kHz	$7 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$1.3 \cdot 10^{-3} \cdot U$		
		50 kHz – 100 kHz	$2.6 \cdot 10^{-2} \cdot U$		
	1 mV – 33 mV	10 Hz – 45 Hz	$1 \cdot 10^{-3} \cdot U$	Generation	On site
		45 Hz – 20 kHz	$5 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$1 \cdot 10^{-3} \cdot U$		
		50 kHz – 100 kHz	$4 \cdot 10^{-3} \cdot U$		
		100 kHz – 500 kHz	$8 \cdot 10^{-3} \cdot U$		
	33 mV – 330 mV	10 Hz – 45 Hz	$5 \cdot 10^{-4} \cdot U$	Generation	On site
		45 Hz – 20 kHz	$3 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$5 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1 \cdot 10^{-3} \cdot U$		
		100 kHz – 500 kHz	$2 \cdot 10^{-3} \cdot U$		
	330 mV – 3.3 V	10 Hz – 45 Hz	$5 \cdot 10^{-4} \cdot U$	Generation	On site
		45 Hz – 20 kHz	$3 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$5 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1 \cdot 10^{-3} \cdot U$		
		100 kHz – 500 kHz	$3 \cdot 10^{-3} \cdot U$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	3.3 V – 33 V	10 Hz – 45 Hz	$5 \cdot 10^{-4} \cdot U$	Generation	On site
		45 Hz – 20 kHz	$3 \cdot 10^{-4} \cdot U$		
		20 kHz – 50 kHz	$5 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$1 \cdot 10^{-3} \cdot U$		
	33 V – 330 V	45 Hz – 20 kHz	$3 \cdot 10^{-4} \cdot U$	Generation	On site
		20 kHz – 50 kHz	$5 \cdot 10^{-4} \cdot U$		
		50 kHz – 100 kHz	$2 \cdot 10^{-3} \cdot U$		
	330 V – 1,000 V	45 Hz – 10 kHz	$3 \cdot 10^{-4} \cdot U$	Generation	On site
	Conversion factor (0.001 – 1) V/V	10 Hz – 100 kHz	$(1 \cdot 10^{-3} - 2 \cdot 10^{-3}) \cdot U/U$		also on site
LF 3 2	Alternating Voltage Ratio				ZTM
	(0.001 – 1) V/V	10 Hz – 100 kHz	$(1 \cdot 10^{-3} - 2 \cdot 10^{-3}) \cdot U/U$	primary voltage 100 mV to 1000 V, secondary voltage 0.1 mV to 1000 V	Also on site
LF 3 3	Alternating High voltage			Measurement and generation	ZTM
	1 – 30 kV	50 Hz	$4.5 \cdot 10^{-3} \cdot U$		Also on site
LF 4 0	Alternating current				ZTM
	10 μ A – 100 μ A	10 Hz – 40 Hz	$3 \cdot 10^{-4} \cdot I$	Measurement	
		40 Hz – 1 kHz	$1.5 \cdot 10^{-3} \cdot I$		
		1 kHz – 10 kHz	$4 \cdot 10^{-3} \cdot I$		
		10 kHz – 30 kHz	$1.5 \cdot 10^{-2} \cdot I$		
	100 μ A – 1 mA	10 Hz – 1 kHz	$2 \cdot 10^{-4} \cdot I$		
		1 kHz – 10 kHz	$4 \cdot 10^{-4} \cdot I$		
		10 kHz – 30 kHz	$7 \cdot 10^{-4} \cdot I$		
	1 mA – 20 A	20 Hz – 10 kHz	$2 \cdot 10^{-4} \cdot I$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		10 kHz – 30 kHz	$2.5 \cdot 10^{-4} /$		
	20 A – 50 A	20 Hz – 5 kHz	$8 \cdot 10^{-4} /$		
	10 μ A – 100 μ A	10 Hz – 40 Hz	$3 \cdot 10^{-4} /$	Calibration (Generation)	
		40 Hz – 1 kHz	$1.5 \cdot 10^{-3} /$		
		1 kHz – 10 kHz	$4 \cdot 10^{-3} /$		
		10 kHz – 30 kHz	$1.5 \cdot 10^{-2} /$		
	100 μ A – 1 mA	10 Hz – 1 kHz	$2.5 \cdot 10^{-4} /$	Calibration (Generation)	
		1 kHz – 10 kHz	$4 \cdot 10^{-4} /$		
		10 kHz – 30 kHz	$7 \cdot 10^{-4} /$		
	1 mA – 100 mA	20 Hz – 30 kHz	$2.5 \cdot 10^{-4} /$		
	100 mA – 11 A	20 Hz – 10 kHz	$2.5 \cdot 10^{-4} /$		
	11 A – 20 A	20 Hz – 5 kHz	$2.5 \cdot 10^{-4} /$		
	20 A – 50 A	20 Hz – 1 kHz	$8 \cdot 10^{-4} /$		
	6 – 120 μ A	10 – 20 Hz	$5 \cdot 10^{-3} /$	Measurement	On site
		20 – 45 Hz	$3 \cdot 10^{-3} /$		
		45 – 5 kHz	$2 \cdot 10^{-3} /$		
	0.12 – 120 mA	10 – 20 Hz	$5 \cdot 10^{-3} /$	Measurement	On site
		20 – 45 Hz	$3 \cdot 10^{-3} /$		
		45 – 100 Hz	$2 \cdot 10^{-3} /$		
		100 Hz – 5 kHz	$1 \cdot 10^{-3} /$		
		5 kHz – 20 kHz	$2 \cdot 10^{-3} /$		
		20 kHz – 50 kHz	$5 \cdot 10^{-3} /$		
		50 kHz – 100 kHz	$8 \cdot 10^{-3} /$		
	0.12 – 1.2 A	10 – 20 Hz	$5 \cdot 10^{-3} /$	Measurement	On site
		20 – 45 Hz	$3 \cdot 10^{-3} /$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		45 Hz – 5 kHz	$2 \cdot 10^{-3} /$		
		5 kHz – 20 kHz	$4 \cdot 10^{-3} /$		
		20 kHz – 50 kHz	$1.5 \cdot 10^{-2} /$		
	29 – 330 μ A	10 Hz – 1 kHz	$2 \cdot 10^{-3} /$	Generation	On site
		1 kHz – 5 kHz	$3 \cdot 10^{-3} /$		
		5 kHz – 10 kHz	$8 \cdot 10^{-4} /$		
		10 kHz – 30 kHz	$1.5 \cdot 10^{-2} /$		
	0.33 – 3.3 mA	10 Hz – 45 Hz	$2 \cdot 10^{-3} /$	Generation	On site
		45 Hz – 1 kHz	$1 \cdot 10^{-3} /$		
		1 – 5 kHz	$2 \cdot 10^{-3} /$		
		5 – 10 kHz	$5 \cdot 10^{-3} /$		
		10 – 30 kHz	$9 \cdot 10^{-3} /$		
	3.3 – 33 mA	10 – 20 Hz	$2 \cdot 10^{-3} /$	Generation	On site
		20 – 45 Hz	$1 \cdot 10^{-3} /$		
		45 Hz – 1 kHz	$5 \cdot 10^{-4} /$		
		1 kHz – 5 kHz	$8 \cdot 10^{-4} /$		
		5 kHz – 10 kHz	$2 \cdot 10^{-3} /$		
		10 kHz – 30 kHz	$4 \cdot 10^{-3} /$		
	33 – 330 mA	10 – 20 Hz	$2 \cdot 10^{-3} /$	Generation	On site
		20 – 45 Hz	$1 \cdot 10^{-3} /$		
		45 Hz – 1 kHz	$5 \cdot 10^{-4} /$		
		1 – 5 kHz	$1 \cdot 10^{-3} /$		
		5 – 10 kHz	$2 \cdot 10^{-3} /$		
		10 – 30 kHz	$4 \cdot 10^{-3} /$		
	0.33 – 1.1 A	10 – 45 Hz	$2 \cdot 10^{-3} /$	Generation	On site
		45 Hz – 1 kHz	$6 \cdot 10^{-4} /$		
		1 – 5 kHz	$6 \cdot 10^{-3} /$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		5 – 10 kHz	$2.5 \cdot 10^{-2} \cdot I$		
	1.1 – 3 A	40 – 45 Hz	$2 \cdot 10^{-3} \cdot I$		
		45 Hz – 1 kHz	$6 \cdot 10^{-4} \cdot I$		
		1 kHz – 5 kHz	$6 \cdot 10^{-3} \cdot I$		
		5 kHz – 10 kHz	$2.2 \cdot 10^{-2} \cdot I$		
	3 – 11 A	45 Hz – 5 kHz	$1 \cdot 10^{-3} \cdot I$	Generation	On site
		5 kHz – 10 kHz	$2.5 \cdot 10^{-2} \cdot I$		
	11 – 20.5 A	45 Hz – 5 kHz	$2 \cdot 10^{-3} \cdot I$	Generation	On site
		5 kHz – 10 kHz	$2.5 \cdot 10^{-2} \cdot I$		
	100 mA – 20 A	20 Hz – 1000 Hz	$4 \cdot 10^{-3} \cdot I$	Generation, only for current clamps / probes	Also on site
	20 A – 1000 A	30 Hz – 60 Hz	$8 \cdot 10^{-3} \cdot I$		
	Conversion factor (0.001 – 1) V/A	20 Hz – 1000 Hz	$4 \cdot 10^{-3} \cdot U/I$		also on site
LF 4 2	Alternating Current Ratio				Also on site
	(0.001 – 1) V/A	20 Hz – 1000 Hz,	$4 \cdot 10^{-3} \cdot U/I$	primary current 100 mA to 1000 A, secondary voltage 0.1 mV to 1000 V, >20 A 30 to 60 Hz	
LF 6 1	Resistance				ZTM
	0.08 mΩ		$1.5 \cdot 10^{-4} \cdot R$	Generation	
	0.2 mΩ; 0.4 mΩ; 0.8 mΩ		$1 \cdot 10^{-4} \cdot R$		
	1 mΩ		$3.5 \cdot 10^{-5} \cdot R$		
	10 mΩ		$1.5 \cdot 10^{-5} \cdot R$		
	100 mΩ		$5 \cdot 10^{-6} \cdot R$		
	1; 10; 100; 1,000 Ω		$3 \cdot 10^{-6} \cdot R$		
	10 kΩ		$1 \cdot 10^{-6} \cdot R$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	100 kΩ		$4 \cdot 10^{-6} \cdot R$		
	1 MΩ		$6 \cdot 10^{-6} \cdot R$		
	10 MΩ		$8 \cdot 10^{-6} \cdot R$		
	100 MΩ		$5.5 \cdot 10^{-5} \cdot R$		
	0 Ω		$1 \cdot 10^{-3} \Omega$	Generation	Also on site
	(0.0001 – 11) Ω		$3.2 \cdot 10^{-5} \cdot R + 1 \cdot 10^{-3} \Omega$		
	(11 – 33) Ω		$6 \cdot 10^{-5} \cdot R$		
	(33 – 110) Ω		$3.3 \cdot 10^{-5} \cdot R$		
	110 Ω – 110 kΩ		$2.8 \cdot 10^{-5} \cdot R$		
	(0.1 – 1.1) MΩ		$3 \cdot 10^{-5} \cdot R$		
	(1.1 – 3.3) MΩ		$6 \cdot 10^{-5} \cdot R$		
	(3.3 – 11) MΩ		$1.2 \cdot 10^{-4} \cdot R$		
	(11 – 33) MΩ		$3 \cdot 10^{-4} \cdot R$		
	(33– 110) MΩ		$5 \cdot 10^{-4} \cdot R$		
	(110 – 330) MΩ		$3 \cdot 10^{-3} \cdot R$		
	(0.33 – 1.1) GΩ		$1.2 \cdot 10^{-2} \cdot R$		
	0.08 mΩ		$1.5 \cdot 10^{-4} \cdot R$	Measurement	
	1 mΩ		$6 \cdot 10^{-5} \cdot R$		
	10 mΩ		$5 \cdot 10^{-5} \cdot R$		
	100 mΩ		$3 \cdot 10^{-5} \cdot R$		
	1 Ω		$6 \cdot 10^{-6} \cdot R$		
	10; 100; 1,000 Ω		$3 \cdot 10^{-6} \cdot R$		
	10 kΩ		$1 \cdot 10^{-6} \cdot R$		
	100 kΩ		$4 \cdot 10^{-6} \cdot R$		
	1 MΩ		$6 \cdot 10^{-6} \cdot R$		
	10 MΩ		$1 \cdot 10^{-5} \cdot R$		
	100 MΩ		$6 \cdot 10^{-5} \cdot R$		
	0.08 mΩ – 1 mΩ		$1.5 \cdot 10^{-4} \cdot R$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	1 mΩ – 1 Ω		$3.5 \cdot 10^{-5} \cdot R$		
	1 Ω – 2 Ω		$3 \cdot 10^{-5} \cdot R$		
	2 Ω – 20 Ω		$2 \cdot 10^{-5} \cdot R$		
	20 Ω – 200 kΩ		$5 \cdot 10^{-6} \cdot R$		
	200 kΩ – 2 MΩ		$1 \cdot 10^{-5} \cdot R$		
	2 MΩ – 20 MΩ		$5 \cdot 10^{-5} \cdot R$		
	20 MΩ – 200 MΩ		$5 \cdot 10^{-4} \cdot R$		
	(0.1 – 10) Ω		$2 \cdot 10^{-5} \cdot R$	Measurement	on site
	(10 – 100) Ω		$1.5 \cdot 10^{-5} \cdot R$		
	(0.1 – 1) kΩ		$1 \cdot 10^{-5} \cdot R$		
	(1 – 10) kΩ		$1 \cdot 10^{-5} \cdot R$		
	(10 – 100) kΩ		$1 \cdot 10^{-5} \cdot R$		
	(0.1 – 1) MΩ		$1.5 \cdot 10^{-5} \cdot R$		
	(1 – 10) MΩ		$5 \cdot 10^{-5} \cdot R$		
	(10 – 100) MΩ		$4 \cdot 10^{-4} \cdot R$		
	(100 – 200) MΩ		$4 \cdot 10^{-3} \cdot R$		
LF 6 4	Capacitance				ZTM
	1 pF	1 kHz	$1.5 \cdot 10^{-4} \cdot C$	Generation	
	10 pF	1 kHz	$4 \cdot 10^{-5} \cdot C$		
	100 pF; 1,000 pF	1 kHz	$1.5 \cdot 10^{-5} \cdot C$		
	10 nF	1 kHz	$1 \cdot 10^{-4} \cdot C$		
	100 nF	1 kHz	$1 \cdot 10^{-4} \cdot C$		
	1 μF	1 kHz	$2.5 \cdot 10^{-4} \cdot C$		
	1 pF – 10 pF	1 kHz	$1.2 \cdot 10^{-5} \cdot C$	Measurement, $D < 0.01$	
	10 pF – 1 nF	1 kHz	$4 \cdot 10^{-5} \cdot C$		
	1 nF – 10 nF	1 kHz	$7 \cdot 10^{-5} \cdot C$		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020** to **01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	10 nF – 100 nF	1 kHz	$1.5 \cdot 10^{-4} \cdot C$		
	100 nF – 1 μ F	1 kHz	$3.3 \cdot 10^{-4} \cdot C$		
LF 6 7	Inductance			Measurement and generation	ZTM
	100 μ H	1 kHz	$1.5 \cdot 10^{-3} \cdot L$		
	1 mH	1 kHz	$5 \cdot 10^{-4} \cdot L$		
	10 mH	1 kHz	$5 \cdot 10^{-4} \cdot L$		
	100 mH	1 kHz	$5 \cdot 10^{-4} \cdot L$		
	1 H	1 kHz	$5 \cdot 10^{-4} \cdot L$		
	1 H	400 Hz	$5 \cdot 10^{-4} \cdot L$		
RF 0 0	High Frequency electricity				
RF 2 1	Reflection coefficient				ZTM
	linear magnitude $ \Gamma $	(0.05 – 2) GHz	$0.005 + 0.004 \cdot \Gamma $	N connector. Best accuracy for a test object VSWR of maximum 1.04	
		(>2 – 18) GHz	$0.012 + 0.020 \cdot \Gamma $		
		(0.05 – 2) GHz	$0.006 + 0.007 \cdot \Gamma $	PC 3.5 connector. Best accuracy for a test object VSWR of maximum 1.06	
		(>2 – 18) GHz	$0.017 + 0.022 \cdot \Gamma $		
		(>18 – 26.5) GHz	$0.029 + 0.021 \cdot \Gamma $		
	VSWR				
		(0.05 – 2) GHz	0.011	N connector. Best accuracy for a test object VSWR of maximum 1.04	
		(>2 – 18) GHz	0.024		
		(0.05 – 2) GHz	0.011	PC 3.5 connector. Best accuracy for a test object VSWR of maximum 1.06	

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		(>2 – 18) GHz	0.034		
		(>18 – 26.5) GHz	0.06		
RF 2 2	Attenuation				
	(10 – 30) dB	(0.05 – < 1) GHz	0.05 dB	3) measured with measuring receiver, N or PC 7 connector	
		(1 – 14) GHz	0.10 dB		
		(> 14 – 18) GHz	0.15 dB		
	(> 30 – 60) dB	(0.05 – < 1) GHz	0.07 dB		
		(1 – 16) GHz	0.10 dB		
		(> 16 – 18) GHz	0.15 dB		
	(3 – 10) dB	(0.05 – <1) GHz	0.07dB	4) Measured with VNA, N connector	
		(1 – 18) GHz	0.14 dB		
	(>10 – 20) dB	(0.05 – <1) GHz	0.09 dB		
		(1 – 18) GHz	0.15 dB		
	(>20 – 40) dB	(0.05 – <1) GHz	0.12 dB		
		(1 – 18) GHz	0.17 dB		
	(>40 – 50) dB	(0.05 – 18) GHz	0.22 dB		
	(>50 – 60) dB	0.05 GHz	0.32 dB		
		(>0.05 – 18) GHz	0.26 dB		
	(3 – 20) dB	(0.05 – <1) GHz	0.08 dB	4) Measured with VNA, PC 3.5 connector	
		(1 – 20) GHz	0.15 dB		
		(>20 – 26.5) GHz	0.17 dB		
	(>20 – 40) dB	(0.05 – 20) GHz	0.17 dB		
		(>20 – 26.5) GHz	0.19 dB		
	(>40 – 50) dB	(0.05 – 20) GHz	0.19 dB		
		(>20 – 26.5) GHz	0.21 dB		
	(>50 – 60) dB	0.05 GHz	0.32 dB		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		(>0.05 – 0.5) GHz	0.24 dB		
		(>0.5 – 20) GHz	0.22 dB		
		(>20 – 26.5) GHz	0.24 dB		
	(10 – 50) dB	(0.05 – 1) GHz	0.04 dB	Calibration with a step attenuator, relative to 0 dB	
	(>50 – 60) dB	(0.05 – 1) GHz	0.05 dB		
	(>60 – 70) dB	(0.05 – 1) GHz	0.10 dB		
	(>70 – 80) dB	(0.05 – 1) GHz	0.20 dB		
RF 3 0	High frequency Power				ZTM
	Calibration factor	(100 – 500) kHz	(2.0 – 1.2) %	1), 2), N connector. Nominal 1 mW	
		500 kHz – 18 GHz	(1.2 – 3.0) %		
		(10 – 50) MHz	(2.7 – 2.1) %	1), 2), N connector. Nominal 1 µW	
		50 MHz – 18 GHz	(2.1 – 3.6) %		
		(10 – 50) MHz	(2.8 – 2.1) %	1), 2). PC 3.5 connector. Nominal 1 mW	
		50 MHz – 26.5 GHz	(2.1 – 3.0) %		
	Absolute power 1 mW	50 MHz	0.004 mW	N connector, measurement and generation	
	Absolute power 0 dBm	50 MHz	0.018 dB		
	Absolute power 0 to -10 dBm	100 kHz	0.13 dB	4) BNC connector. Measurement with power sensor (e.g. generator)	
		>100 kHz - 1 GHz	0.10 dB		
		100 kHz	0.13 dB	4) N female or PC 7 connector. Measurement with power sensor (e.g. generator)	
		>100 kHz – 6 GHz	0.10 dB		
		(>6 – 14) GHz	0.13 dB		
		(>14 – 18) GHz	0.15 dB		
		10 MHz	0.20 dB	4) PC 3.5 male or female connector. Measurement	
		>10MHz – 6 GHz	0.12 dB		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		(>6 – 18) GHz	0.15 dB	with power sensor (e.g. generator)	
		(>18 – 26.5) GHz	0.20 dB		
	Absolute power -10 to -90 dBm	(2.5 – 1000) MHz	0.20 dB	4) BNC connector. Measurement with measuring receiver (e.g. generator)	
	Absolute power -90 to -110 dBm	(2.5 – 1000) MHz	0.20 dB		
	Absolute power -10 to -90 dBm	(2.5 – 1300) MHz	0.20 dB	4) N female or PC 7 connector. Measurement with measuring receiver (e.g. generator)	
		(>1.3 – 2.6) GHz	0.25 dB		
	Absolute power -90 to -110 dBm	(2.5 – 1300) MHz	0.20 dB		
		(>1.3 - 2.6) GHz	0.25 dB		
	Absolute power -10 to -90 dBm	(10 – 1300) MHz	0.20 dB	4) PC 3.5 male or female connector. Measurement with measuring receiver (e.g. generator)	
		(>1.3 – 10) GHz	0.25 dB		
		(>10 – 21) GHz	0.35 dB		
		(>21 – 24) GHz	0.40 dB		
		(>24 – 26) GHz	0.60 dB		
	Absolute power -90 to -110 dBm	(10 – 1300) Mhz	0.25 dB		
		(>1.3 – 10) GHz	0.30 dB		
		(>10 – 21) GHz	0.35 dB		
		(>21 – 24) GHz	0.40 dB		
		(>24 – 26) GHz	0.60 dB		
	Absolute power 0 to -10 dBm	100 kHz	0.16 dB	4) BNC connector. Calibration with splitter and power sensor (e.g. spectrum analyser)	
		>100 kHz – 6 GHz	0.13 dB		
		100 kHz	0.16 dB	4) N male or female or PC 7 connector. Calibration with splitter and power sensor (e.g. spectrum analyser)	
		>100 kHz – 6 GHz	0.13 dB		
		(>6 – 12) GHz	0.16 dB		
		(>12 – 18) GHz	0.19 dB		
		10 MHz – 6 GHz	0.13 dB		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020** to **01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		(>6 – 12) GHz	0.16 dB	4) PC 3.5 male connector. Calibration with splitter and power sensor (e.g. spectrum analyser)	
		(>12 – 18) GHz	0.19 dB		
		(>18 – 26.5) GHz	0.24 dB		
	Absolute power -10 to -90 dBm	50 MHz	0.25 dB	4) BNC connector. Calibration with splitter and measuring receiver (e.g. spectrum analyser)	
	Absolute power -90 to -100 dBm	50 MHz	0.30 dB		
	Absolute power -10 to -90 dBm	50 MHz	0.25 dB	4) N male or female or PC 7 connector. Calibration with splitter and measuring receiver (e.g. spectrum analyser)	
	Absolute power -90 to -100 dBm	50 MHz	0.30 dB		
	Absolute power -10 to -90 dBm	50 MHz	0.25 dB	4) PC 3.5 male connector. Measurement with splitter and measuring receiver (e.g. spectrum analyser)	
	Absolute power -90 to -100 dBm	50 MHz	0.30 dB		
TF 0 0	Time and Frequency				
TF 2 1	Frequency				ZTM
	100 kHz		$1 \cdot 10^{-11} \cdot f$	Measurement measuring time $\tau \geq 1,000$ s	
	1 MHz		$1 \cdot 10^{-11} \cdot f$		
	5 MHz		$1 \cdot 10^{-11} \cdot f$		
	10 MHz		$1 \cdot 10^{-11} \cdot f$		
	0.1 Hz – 1 Hz		12 μ Hz	Measurement. Generation measuring time $\tau \geq 20$ s	
	1 Hz – 10 Hz		12 μ Hz		
	10 Hz – 100 Hz		12 μ Hz – 1.2 μ Hz		
	100 Hz – 1 kHz		1.2 μ Hz		
	1 kHz – 10 kHz		1.2 μ Hz		
	10 kHz – 100 kHz		1.2 μ Hz		
	100 kHz – 1 MHz		1.2 μ Hz – 12 μ Hz		
	1 MHz – 10 MHz		12 μ Hz – 0.12 mHz		

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020** to **01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	10 MHz – 100 MHz		0.12 mHz – 1.2 mHz		
	100 MHz – 1 GHz		1.2 mHz – 12 mHz		
	1 GHz – 3 GHz		12 mHz – 14 mHz		
	3 GHz – 27.5 GHz		1.2 Hz		
TF 2 2	Time interval			Measurement	ZTM
	100 ps – 1 ns		$1.2 \cdot 10^{-9} \cdot T$		
	1 ns – 10 ns		$1.2 \cdot 10^{-9} \cdot T$		
	10 ns – 100 ns		$1.2 \cdot 10^{-9} \cdot T$		
	100 ns – 1 μs		$1.2 \cdot 10^{-9} \cdot T$		
	1 μs – 10 μs		$1.2 \cdot 10^{-9} \cdot T$		
	10 μs – 100 μs		$1.2 \cdot 10^{-9} \cdot T$		
	100 μs – 1 ms		$1.2 \cdot 10^{-9} \cdot T$		
	1 ms – 10 ms		$1.2 \cdot 10^{-9} \cdot T$		
	10 ms – 100 ms		$1.2 \cdot 10^{-8} \cdot T - 1.2 \cdot 10^{-6} \cdot T$		
	100 ms – 1 s		$1.2 \cdot 10^{-6} \cdot T - 1.2 \cdot 10^{-5} \cdot T$		
	1 s – 10 s		$1.2 \cdot 10^{-5} \cdot T - 1.2 \cdot 10^{-4} \cdot T$		
				Measurement	
	0.1 μs – 100 ms		$1 \cdot 10^{-6} \cdot T + 10 \text{ ns}$	Equipment with separated electrical start and stop inputs.	
	100 ms – 1 s		$1 \cdot 10^{-5} \cdot T + 10 \text{ ns}$		
	1 s – 10 s		$1 \cdot 10^{-4} \cdot T + 10 \text{ ns}$		
OQ 1 0	Optical quantities				
OQ 13	Optical wavelength	1511 – 1542 nm	0.2 pm	Calibration of wavelength with a wavelength reference cell, fixed wavelengths	

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020 to 01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
		840 – 860 nm 1270 – 1650 nm	0.4 pm 0.4 pm	Calibration of wavelength in combination with a reference wavelength meter	
		840 – 860 nm 1270 – 1650 nm	0.4 pm 0.4 pm	Measurement of wavelength with a reference wavelength meter	
		600 – 1530 nm	300 ppm	Measurement of wavelength with an optical spectrum analyser	
OQ 1 5	Optical Power				ZTM
	-5 dBm to -55 dBm (316 µW to 3.16 nW)	850 nm	0.09 dB (≈2.0 %)	Measurement and Calibration	
	-5 dBm to -55 dBm (316 µW to 3.16 nW)	1300 nm	0.13 dB (≈3.0 %)		
	+3 dBm to -55 dBm (2 mW – 3.16 nW)	1310 nm	0.09 dB (≈2.0 %)		
	+3 dBm to -55 dBm (2 mW – 3.16 nW)	1550 nm	0.09 dB (≈2.0 %)		
	-5 dBm to -55 dBm (316 µW – 3.16 nW)	1625 nm	0.10 dB (≈2.3 %)		
	-5 dBm to -55 dBm (316 µW to 3.16 nW)	850 nm	0.05 dB	Linearity calibration relative to -10 dBm	
	-5 dBm to -55 dBm (316 µW to 3.16 nW)	1300 nm	0.05 dB		
	+3 dBm to -55 dBm (2 mW- 3.16 nW)	1310 nm	0.05 dB		
	+3 dBm to -55 dBm (2 mW- 3.16 nW)	1550 nm	0.05 dB		
	-5 dBm to -55 dBm ((316 µW – 3.16 nW)	1625 nm	0.05 dB		

Annex to declaration of accreditation (scope of accreditation)
Normative document: EN ISO/IEC 17025:2017
Registration number: **K 052**

of **TRESCAL Zoetermeer B.V.**
Technical Operations

This annex is valid from: **05-06-2020** to **01-03-2022**

Replaces annex dated: **19-02-2020**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	0 dB to 45 dB	850 nm	0.06 dB	Measurement of incremental loss	
	0 dB to 45 dB	1300 nm	0.06 dB		
	0 dB to 55 dB	1310 nm	0.05 dB		
	0 dB to 55 dB	1550 nm	0.05 dB		
	0 dB to 50 dB	1625 nm	0.05 dB		

Electrical and optical calibrations are performed at nominal 23 °C.

The CMC in RF and Microwave measurements are applicable to instruments with a characteristic impedance of nominal 50 Ohm

- 1) Measurements are performed at a fixed set of measurement frequencies;
- 2) Calibration factor is applicable to measurements relative to 50 MHz;
- 3) CMC is calculated for a test object VSWR of 1.01 and the maximal VSWR for the uncertainty calculation is 1.35;
- 4) CMC is calculated for a test object with a typical VSWR of 1 to 1.27;

The measurements are carried out inside Trescal BV 's laboratory or in another location (on site).